

GI SERIES INVERTERS



	PA-GI2000	PA-GI3000	PA-GI3500
MAX OUTPUT	2000 W	3000 W	3500 W
RUNNING OUTPUT	1600 W	2800 W	3000 W
ENGINE	79CC 4-STROKE	212CC 4-STROKE	212CC 4-STROKE
LOW OIL SHUTDOWN	YES	YES	YES
PARALLEL CAPACITY	YES	YES	YES
START SYSTEM	RECOIL	RECOIL	ELECTRIC
FUEL TANK	4.0 L	10.0 L	10.0 L
AUTO IDLE DOWN	YES	YES	YES
NOISE LEVEL @ 100% LOAD	59 DB	59 DB	60 DB
RUN TIME @ 25% LOAD	7 HRS	15 HRS	16 HRS
WEIGHT / SHIPPING	49 LBS / 53 LBS	85 LBS / 93 LBS	98 LBS / 105 LBS
GENERATOR WARRANTY	2 YRS	2 YRS	2 YRS
RECEPTACLES	1 X 120V 20A DUPLEX 1 X 12V DC 8.0A	1 X 120V GFCI 20A DUPLEX 1 X 120V TWISTLOCK 1 X 12V DC 8.0A	1 X 120V GFCI 20A DUPLEX 1 X 120V 30A TWISTLOCK 1 X 12V DC 8.0A



▶ PA-GI2000



▶ PA-GI3000



▶ PA-GI3500

